

GR



PIR

μ

tamper

μ

μ

12 μ

μ

μ

2 μ

μμ

μ

1

Learn/Test

μ

- μ

2

Tamper

Tamper

3

Test/Normal (JP1)

3 pins

μ

:



2


pins

test.




pins,

(Normal).



[illegible]

- , μ μ μ μ .
- μ μ μ μ μ .
- (μ μ μ μ) .
- μ μ μ μ μ .



- μ .
- pins JP1. Test Mode, μ LED
- μ .
- $\mu\mu$.
- μ LED
- $\mu\mu$ pins JP1)
- Normal Mode (μ pins JP1)

- : μ μ 2 2,5 μ μ .
- μ μ 3 5m, 1,9 μ 2 μ .
- μ μ μ μ μ μ .
- μ μ μ μ μ (. . air conditioners, μ)
- μ μ μ μ ()

Made in TAIWAN

Head Office: **Elkron S.p.A.** Via Cimarosa, 39 – 10154 TORINO (TO) ITALY

Tel. +39(0)11 3986711 Fax +39(0)11 3986790; web: www.elkron.it ; e-mail: info@elkron.it

Milan Office: Via Gadames, 109 – 20151 MI ; Tel: +39(0)2 334491 – Fax: +39(0)2 33449213

